

405207

STRONG dálkový ovládač 4 zónový

Přehled

- 4 zónový dálkový ovládač
- Citlivé nastavení intenzity světla
- přenosová frekvence 2,4 GHz, dosah až 30 m (ve volném prostoru)
- možnost připojení více řídicích jednotek
- Napájení 2 AAA baterie
- LED kontrolka

Technické parametry

Přenosová frekvence	2,4 GHz
Napětí	3V (2 x AAA)
Pracovní proud	< 20 mA
Spotřeba naprázdno	< 10 µA
Výdrž baterie (max.)	< 1 rok
Dosah	30 m
Pracovní prostředí	- 30°C ~ 55°C
Rozměry	122x53x17,5 ..
Váha	60 g

Popis ovládače




-  Zapnutí / vypnutí všech zón
-  Pohybem po ploše lze měnit intenzitu světla

-  Krátký stisk - zapnutí příslušné zóny
Dlouhý stisk (nad 2sekundy) - vypnutí příslušné zóny

-  : 25%, 50%, 75%, 100% nastavení jasu zvolené zóny

-  Dlouhý stisk (nad 2 sekundy) - uložení aktuálního nastavení
Krátký stisk - spuštění uloženého nastavení

Rozměry



Indikace LED

- Při zapnutí světel svítí LED modře, při vypnutí se rozsvítí červeně
- Pokud je zvolena nepřípustná kombinace, svítí kontrolka červeně
- Kontrolka svítí při úpravě jasu
- Kontrolka svítí pouze několik sekund, pak zhasne z důvodu šetření baterie

Párování

Ovládač využívá technologii 2,4 GHz, pro využití je nezbytné spárování s příslušnou řídicí jednotkou
Párování tlačítkem Match na řídicí jednotce

Párování > stiskněte tlačítko Match a do 5 s stiskněte tlačítko zóny, které chcete jednotku přiřadit
Vymazání párování - stiskněte tlačítko Match na déla jak 5 s. Veškeré párování bude vymazáno

Párování dálkovým ovládačem

Párování
Vypněte na chvíli napájení, pak zapněte a do 5 s stiskněte na dálkovém ovládači rychle 3 x tlačítko zóny, které chcete jednotku přiřadit.
Vymazání párování
Vypněte na chvíli napájení, pak zapněte a do 5 s stiskněte na dálkovém ovládači rychle 5 x tlačítko off/on. Při správném průběhu mazání světlo 5 x blikne.

Bezpečnostní informace


Výrobek musí být instalován a servisován kvalifikovanou osobou.
Výrobek není vodotěsný (IP20). Instalujte pouze na chráněná místa.
Dbejte na správnou polaritu vložených baterií (2xAAA), při delším nepoužívání vyjměte baterie.
V případě, že ovládač při funkčních bateriích nereaguje, proveďte opětovné spárování dle návodu.



User Guide

4 Zone Dimming RF Remote Controller

Dimension



Operation

- When turn on light, the indicator display blue. when turn off light, the indicator display red.
- When touch the color wheel, the indicator will display the same color.
- When press or touch operation is invalid (If the light is off), the indicator display red.
- To extend battery life, no touch or press key operation after a few seconds, the touch wheel will enter sleep state, you need press any key to make touch wheel quit sleep state.

Match guide

Remote match with 2.4G RF controller, dimming driver, smart lamp and panel controller.

Match with controller(with match key)

1. Match: Short press match key, within 5s, press zone key of the remote.
2. Delete: Long press match key for 5s, delete all matched remote.

Match with controller(without match key), dimming driver or smart lamp

1. Match:
Switch off the power, then switch on power again, short press zone key 3 times on the remote quickly within 5s after power on, the link is done once the light blinks 3 times.
2. Delete:
Switch off the power, then switch on power again, short press zone key 5 times on the remote quickly within 5s after power on, the unlink is done once the light blinks 5 times.

Match with panel controller

1. Match: Turn on light, turn off, immediately press on/off key for 5s, within 5s, press zone key of the remote.
2. Delete: Turn on light, turn off, immediately press on/off key for 10s, delete all matched remote.

Safety information

1. Read all instructions carefully before you begin this installation.
2. When installing battery, pay attention to the battery positive and negative polarity. A long time without the remote control, remove the battery. When remote distance becomes smaller and insensitive, replace the battery.
3. If no response from the receiver, please re-match the remote.
4. Gently handle remote, beware of falling.
5. For indoor and dry location use only.

Summary

- Apply to single color LED controller or smart lamp.
- Black or white version available.
- Ultra sensitive color adjustment touch wheel.
- Adopt 2.4GHz wireless technology, remote distance up to 30m.
- Each remote can match one or more receiver.
- Battery powered (2 x AAA).
- Operate with LED indicator light.

Technical parameter

- Output signal: RF(2.4GHz)
- Working voltage: 3VDC(AAA*2pcs)
- Working current: < 20mA
- Standby current: < 10μA
- Standby time: 12 months
- Remote distance: 30m
- Working temperature: -30°C~55°C
- Dimension: L122×W53×H17.5mm
- Weight: 60g

Key function



: Short press turn on/off all zone light.

: Touch to change current zone brightness.

: Short press select and turn on zone light, long press 2s turn off zone light. Continuous short press multiple zone key, can synchronous select multiple zone.

: 25%, 50%, 75%, 100% brightness for current selected zone.

: Short press run the scene, long press 2s save. 4 zone or channel run or save synchronously.